

# SX-20-K

Stereo Receiver with Phono Input and FM/AM Tuner



REAR PANEL



## DESIGN & BUILD

- › Analogue Discrete 2ch Amplifier
- › 100 W + 100 W High Power Output
- › FM (RDS)/AM Tuner with 30 Presets
- › Phono Input (MM)
- › Speaker A/B Selector
- › FL Display
- › Aluminium Front Panel
- › Sleep Timer
- › Auto Power Down

## AMPLIFIER

- › Power Output (Stereo):
  - 100 W + 100 W (20 Hz-20 kHz, THD 1 %, 8 ohms)
- › THD: 0.02 % (Rated Output -3 dB, 8 ohms, 1 kHz)
- › S/N Ratio:
  - Phono (MM): 80 dB
  - Line (SACD/CD, NETWORK, RECORDER): 100 dB
- › Tone Controls: Bass (100 Hz)/Treble (10 kHz):  $\pm 14$  dB
- › Frequency Response:
  - Phono: 20 Hz-20 kHz,  $\pm 0.5$  dB (RIAA Equalisation) MM
  - Line (SACD/CD, NETWORK, RECORDER) : 5 Hz-100 kHz, 0 dB/-3 dB

## TERMINALS

- › Analogue Audio Input (SACD/CD, NETWORK, RECORDER, PHONO (MM))
- › Audio Output (RECORDER)
- › FM/AM Tuner Antenna
- › Large Speaker A/B Terminals
  - Speaker Impedance: 4-16 ohms (A or B), 8-16 ohms (A+B), 4-16 ohms (Bi-Wire)
- › Headphones Terminal
- › AC Inlet

## SPECIFICATIONS

- › Power Requirements: 220-230 V, 50/60 Hz
- › Power Consumption (Standby): 210 W (0.3 W)
- › Dimensions (W x H x D): 435 x 142.5 x 364 mm
- › Weight: 8.3 kg